

M-L190C LED Mini Magic Ball Light

USER'S MANUAL

Thanks for your choosing our product, please carefully read this manual and operate it obey the specification in order to make sure you can correct and safety installing, operating and maintaining it.

I. Technical Parameters

Voltage: AC90-240V

Frequency: 50/60HZ

Power: 20W

Lamp: 6pcs LEDs

Controller Model: Auto, Sound Activate, DMX512 and Master-slave

Packing Size: 600 *400 *360mm(12pcs)

Net Weight: 0.6KG, Gross Weight: 0.8KG

II. Menu Operation Instructions:

Press “Menu” button to Set, to confirm by press “ENTER” button。 correct by pressing “UP&DOWN” button.

A001	001-512	Function Description
A1-1	A1-1~A1-9	Red and Purple On Mode, Running Program speed from slow to fast
A2-1	A2-1~A2-9	Green and White On Mode, Running Program speed from slow to fast
A3-1	A3-1~A3-9	Blue and Yellow On Mode, Running Program speed from slow to fast
A4-1	A4-1~A4-9	Six color hopping mode, Running Program speed from slow to fast
A5-1	A5-1~A5-9	Gradient mode, Running Program speed from slow to fast
A6-1	A6-1~A6-9	Gradient mode, Running Program speed from slow to fast
A7-1	A7-1~A7-9	Strobe mode, Running Program speed from slow to fast
S1-1	S1-1~S1-20	Sound control strobe
S2-1	S2-1~S1-20	Sound control

III: DMX Channel Operations:

Channel	Channel values	Function Description
CH1	0-255	Dimming
CH2	0-255	Red & purple LED dimming, brightness fade from dark to bright
CH3	0-255	Green& White LED dimming, brightness fade from dark to bright
CH4	0-255	Blue & Orange LED dimming, brightness fade from dark to bright
CH5	0-255	Strobe From fast to low
CH6	0-255	Rotation
CH7	0-9	No Function
	10-196	Auto Program
	197-220	Sound Control Strobe
	221-255	Sound Control

HD AUDIO SYSTEM INC.

ADDRESS : 2112 Lee Ave. South El Monte, CA 91733

TELEPHONE : +1 (626) 433-0357 +1 (844) 223-7809

FAX : +1 (626) 433-0315

EMAIL : info@hdaudiosystem.com