



Maximize Your Performance
Minimize Your Price



The DX-211 G2 is the newest in our DX Series Karaoke amplifiers. Equipped with a 4-pin S-Video plug, the DX-211 G2 is compatible with Karaoke Remote control (sold separately), perfect for use without reaching the amplifier itself. By storing the amplifier in a well ventilated area (e.g. systems room with air ventilation) the amplifier can work at full potential in an appropriate environment, and with the Karaoke Remote compatibility you won't need to run back and forth adjusting the mixer since it can be controlled by remote.



PHYSICAL DIMENSIONS

NET WEIGHT	23.8 lbs / 10.8 Kg
SHIPPING WEIGHT	26 lbs / 11.8 Kg
DIMENSIONS (WxHxD)	17x5.3x14.1 in / 43x13.5x35.8 cm
PACKING DIMENSIONS (WxHxD)	20x8x18.5 in / 50.8x20.3x47 cm



SPECIFICATIONS

POWER OUTPUT	PEAK 500W, RMS 260W (8 ohm); RMS 300W (4 ohm)	
THD	≤0.7%	
FREQUENCY RESPONSE	20Hz~20KHz +/-1dB	
TONE ELECTRICAL CIRCUIT	MUSIC PART BASS Control: 100Hz ± 10dB TREBLE Control: 10kHz ± 10dB	MIC PART BASS Control: +6dB/-16dB TREBLE Control: +6dB/-16dB
INPUT SENSITIVITY/IMPEDANCE	220 mV	
EFFECT	ECHO	
MUSIC INPUT HF/LF	HF (INCREASE/ATTENUATE): ±8 dB LF (INCREASE/ATTENUATE): ±8 dB	
MUSIC INPUT S/N RATIO	≥80 dB	
POWER CONSUMPTION	AC 110V/~60Hz (North America Market) AC 220V/~50Hz (Asia or Europe Market)	