

LED 194s LED Mini Butterfly Light

USER'S MANUAL

Thanks for your choosing our product, please carefully read this manual and operate it obey the specification in order to make sure you can correct and safety installing, operating and maintaining it.

I. Technical Parameters

Voltage: AC90-240V

Frequency: 50/60HZ

Power: 20W

Lamp: 4pcs 3W LEDs

Controller Model: Auto, Sound Activate, DMX512 and Master-slave

Packing Size: 540 *450 *510mm(12pcs)

Net Weight: 1.5KG, Gross Weight: 1.8KG

II. Menu Operation Instructions:

Press “Menu” button to Set, to confirm by press “ENTER” button. correct by pressing “UP&DOWN” button.

A001	001-512	Function Description
A1-1	A1-1~A1-9	Red color Mode, Rotation speed from slow to fast
A2-1	A2-1~A2-9	Green color Mode, Rotation speed from slow to fast
A3-1	A3-1~A3-9	Blue color Mode, Rotation speed from slow to fast
A4-1	A4-1~A4-9	White color Mode, Rotation speed from slow to fast
A5-1	A5-1~A5-9	RGB color Gradient mode, Rotation speed from slow to fast
A6-1	A6-1~A6-9	Gradient mode, Rotation speed from slow to fast
A7-1	A7-1~A7-9	Gradient mode, Rotation speed from slow to fast
A8-1	A8-1~A8-9	Strobe mode, Rotation speed from slow to fast
S1-1	S1-1~S1-20	Sound control model 1
S2-1	S2-1~S1-20	Sound control model 2

III: DMX Channel Operations:

Channel	Channel values	Function Description
CH1	0-255	Dimming
CH2	0-255	Red color dimming
CH3	0-255	Green color dimming
CH4	0-255	Blue color dimming
CH5	0-255	White color dimming
CH6	0-9	No Function
	10-255	Strobe
CH7	0-5	No rotation
	6-127	Motor positioning go
	128-255	Motor rotation speed from slow to fast
CH8	0-9	Manual mode: Turn on CH1-CH7
	10-72	RGBW color Fade
	73-197	RGBW color Pulse Jump

	198-220	Sound Control Model 1
	221-255	Sound Control Model 2

HD AUDIO SYSTEM INC.

ADDRESS : 2112 Lee Ave. South El Monte, CA 91733

TELEPHONE : +1 (626) 433-0357 +1 (844) 223-7809

FAX : +1 (626) 433-0315

EMAIL : info@hdaudiosystem.com