Passionate about Music www.BetterMusicBuilder.com DX-333 G2 MIXING AMPLIFIER



Maximize Your Performance Minimize Your Price







The Dynamic Fusion Amplifier DX-333 G2 features many recognizable functions users enjoyed on its best-selling predecessor. It features a user-friendly interface designed with fast access to effects control in mind. There's built-in Equalizer for music and vocal with a 9-Steps Music Key Control and independent microphone effects control. A convenient Volume Reset function allows user to choose a preset music volume. The DX-333 G2 is equipped with a standard built-in Smart Fan that automatically activates when high temperature is detected to keep the machine running cool and extend product life.



NET WEIGHT	25.6 Lbs / 11.6 Kg
SHIPPING WEIGHT	27.6 lbs / 12.5 Kg
DIMENSIONS (WxHxD)	17x5x12.6 in / 43x13x32 cm
PACKING DIMENSIONS (WxHxD)	20.3x7.9x15.2 in / 51.5x20x38.5 cm



POWER OUTPUT	PEAK: 700W @8ohm; 960W @4ohm RMS: 300W @8ohm; 400W @4ohm
T.H.D.	0.5%
FREQUENCY RESPONSE	20Hz~20KHz +/-1dB
S/N RATIO	65 dB
TONE BALANCE CONTROL	+/-12dB
NOISE LEVEL	<10mV
BALANCE INPUT	+/-1.5dB
SPLIT LEVEL	>35dB
MIC SENSITIVITY	<30mV
MIC FREQUENCY	100Hz~2.5kHz
BLUETOOTH	Version 2.0
DIGITAL AUDIO FILE COMPATIBLILTY	MP3/WMA
MAXIMUM USB/SD CARD SUPPORT	16 GB
POWER CONSUMPTION	AC 110V/~60Hz (North America) AC 220V/~50Hz (Asia or Europe)